

Shutdown with shelly plug s

I will switch off the "Shelly plug s" after the shutdown of the device with a delay of 30 seconds.

Create file with `sudo nano /usr/lib/systemd/system-shutdown/systemd-halt.service` .

```
[Unit]
Description=Run mycommand at shutdown
Requires=network.target
DefaultDependencies=no
Before=shutdown.target

[Service]
Type=oneshot
RemainAfterExit=true
ExecStart=/bin/true
ExecStop=curl -u username:password "http://IP-Address/relay/0?turn=on&timer=30"

[Install]
WantedBy=multi-user.target
```

After that enable service with `sudo systemctl enable /usr/lib/systemd/system-shutdown/systemd-halt.service` .

Revision #7

Created 2023-06-28 06:35:56 UTC by sylvio

Updated 2023-07-21 18:04:34 UTC by sylvio